



No specialized wiring is required, uses Z224FT4 (hardwire/JKT)

**NOTE** Depending upon the type of wiring installation you have selected, install the diodes IN4005 (included) in accordance to the wiring diagram.

Install the microphones away from noise such as ; ventilation ducts, refrigerator, etc...

Additional external microphones are to be hooked-up to the terminal output at the rear of the wall plate. Make sure that the wires are connected properly.

Ex: stranded to neg.(-) / insulated to pos.(+)

You can remove the microphone PCBoard from it's original wall plate and install it in other devices. Use extreme CAUTION when doing so.

Before powering-up the XP804 unit, make sure that all components are correctly hooked-up, that is, the microphones, the RCA plugs, etc...

- Power consumption: 16.48ma

- Standard flush mount microphones:

    Omnidirectional

    Frequency response = 20-12K

    Sensitivity = -64dB (-42dB+3dB)

    Current drain + 0.5mA

- Weight: 4.85 ounces

- Dimensions: Length 5.1" inches Width 2.6" inches Height 1.0" inches